

## Firmware update instructions for the Conceptronic C300BRS4 Version 2.0 firmware version 2.02

---

1. Login to the C300BRS4 Version 2.0. The default settings are:

IP address : <http://192.168.0.1>  
User name : admin  
Password : admin

2. Point to 'Tools' in the top menu bar and click on 'Firmware' from the drop down menu.
3. Click on the 'Browse' button to locate the firmware file. When done it will appear in the 'File path' field.

Firmware file name : C300BRS4\_V2\_FW\_UPD\_v2.02.bin

4. Click on 'Apply'. Confirm the message that appears by clicking 'OK'.
5. The upgrade procedure will start.
6. When the upgrade procedure is completed the C300BRS4 Version 2.0 will reboot automatically.
7. A factory reset is needed to make sure the firmware becomes fully functional:

***Note:** When a factory reset is initiated, all previous settings will be lost. As a result, the C300BRS4 will need to be reconfigured afterwards.*

- Login to the C300BRS4 Version 2.0 as described at point 1.
  - Point to 'Tools' in the top menu bar and select 'System' from the drop down menu.
  - Click on 'Reset'. Confirm the message that appears by clicking 'OK'.
8. The C300BRS4 Version 2.0 is now fully updated and ready to be used. Don't forget to reconfigure your C300BRS4 Version 2.0 before use (if needed).

***Note:** It is recommended not to load configuration files that have been created with previous firmware versions. Doing so might result in an unstable C300BRS4 Version 2.0.*



## Conceptronic C300BRS4 Version 2.0 Release Notes Firmware version 2.02

---

### V2.02

- Changed:
    - Improved internal wireless driver.
    - DHCP behavior. When WAN mode is DHCP and no cable is connected, the DHCP server sets the lease time to 60 seconds.
    - Beacon interval value range to 25-1000.
    - Title text of web page changed to "C300BRS4 v2.0 / v3.0".
    - UPnP name changed to "C300BRS4".
    - Description text in wizard changed from "C300BRS4 v2.0" to "C300BRS4".
- 

### V2.00

- Initial release.
-