

Firmware update instructions for the Conceptronic CH3B2E

1. Connect the CH3B2E by use of eSATA or USB to your PC.
2. Open the Steel Vine application, click on 'Edit' -> 'Specify Firmware'.
3. A password is required to proceed, use "admin" as password
4. Click on "Browse" and specify the location of the new firmware "Sil5744_11605.bin"
5. Click on "Install Firmware", the upgrade process will start.
6. When the upgrade process is completed a pop up will appear, choose "Shutdown Now".
7. Your PC will be shutdown, please turn off the CH3B2E and turn on again.
8. Turn on your PC.
9. The CH3B2E is now fully updated and ready for use!

Conceptronic CH3B2E Release Notes

V1.1605

- Added support for 1,5 / 2TB hard drives

V1.1516

Initial release.